What is claimed is:

1.   A method for determining transducer velocities profiles in a disk drive,

comprising:

      determining a first transducer velocity profile in a first direction;

      determining a second transducer velocity profile in a second direction;

5   adjusting said second transducer velocity profile in an amount sufficient such that

a ramp tab does not hit a crash stop at a velocity which might cause mechanical damage

to said disk drivewhen said disk drive loses power during operation while a seek is in

progress.

2.   A method, as claimed in claim 1, wherein said adjusting step includes:

      adjusting a current of a deceleration portion of said second transducer velocity

profile in an amount sufficient such that current available from a back electromotive force

of a spindle motor will decelerate said transducer in an amount sufficient such that said

ramp tab does not bounce off of said crash stop and back over a rotating storage medium

when said disk drive loses power while a seek is in progress.

3.   A method, as claimed in claim 1, wherein said mechanical damage

includes:

      damage to a surface of a rotating storage medium which might result in loss of

data stored on said rotating storage medium.

-25-

4.   A method, as claimed in claim 1, wherein said mechanical damage includes:

damage to said crash stop or damage to said ramp tab.

5.   A method, as claimed in claim 1, wherein said adjusting step includes:

adjusting a current of a deceleration portion of said second transducer velocity profile by a predetermined amount.

6.   A method, as claimed in claim 5, wherein said predetermined amount is approximately 50 percent.

7.   A method, as claimed in claim 1, wherein said adjusting step includes:

adjusting said second transducer velocity profile by a variable amount.

8.   A method, as claimed in claim 7, wherein said adjusting step includes:

calculating said variable amount based on at least one of a target track, power supply voltage, temperature, spindle motor back electromotive force, and positioner gain.

9.   A method, as claimed in claim 7, wherein said variable amount is a derate factor calculated using the equation:

$$Derate\_ \; \text{factor} = \frac{(\text{max}\_\text{track} - \text{tgt}\_\text{track})^2 \times 127}{2^{26} \times \sqrt{2a}} + 0.5$$

where *max_track* is the number of the maximum track, *tgt_track* is the number of the target track, and *a* is the deceleration of the transducer according to said deceleration portion of said seek velocity profile.

10. A method, as claimed in claim 8, wherein:

said adjusting step further includes calculating a warping factor and applying said warping factor to said second transducer velocity profile.

11. A method, as claimed in claim 10, wherein:

said warping factor is determined based on at least one of a seek length, a transducer velocity, and a voice coil motor back electromotive force.

12. A method, as claimed in claim 11, wherein said warping factor is determined according to the following equation:

$$Warp\_\text{factor} = \sqrt{2a} \times \sqrt{(1 + Kwarp \times Vel)} \times \text{xtg}$$

5   where *a* is the deceleration of said transducer according to a deceleration portion of said seek velocity profile, *vel* is the velocity of the transducer, *xtg* is said seek length, and *kwarp* is a variable determined by the amount of said voice coil motor back electromotive force.

13.   A disk drive, comprising:

a storage disk having a plurality of concentric tracks for storing data;

a spindle motor for rotating said storage disk;

an actuator arm assembly having a transducer for reading data from said storage

5   disk and having a ramp tab;

a ramp operable to engage said ramp tab and prevent said transducer from

contacting said storage disk when said storage disk is not rotating, said ramp having a

crash stop located at a distal end of said ramp;

a voice coil motor operable to move said actuator arm relative to said storage disk

10   from a starting track to a target track according to a first velocity profile in a first

direction toward said ramp and a second velocity profile in a second direction away from

said ramp in response to a control signal; and

a controller operable to generate said control signal and deliver said control signal

to said voice coil motor such that said first velocity profile is limited such that said ramp

15   tab does hit said crash stop at a velocity which might cause mechanical damage to said

disk drivewhen said disk drive loses power while a seek is in progress.

14.   The disk drive, as claimed in claim 13, wherein said mechanical damage

includes:

damage to a surface of said storage disk which might result in loss of data stored

on said storage disk.

15.   The disk drive, as claimed in claim 13, wherein said mechanical damage includes:

damage to said crash stop or damage to said ramp tab.

16.   The disk drive, as claimed in claim 13, wherein:

a current required for a deceleration portion of said first velocity profile is derated by a factor of approximately 0.5.

17.   The disk drive, as claimed in claim 13, wherein:

said first velocity profile is derated by a variable amount.

18.   The disk drive, as claimed in claim 17, wherein:

said variable amount is determined according to at least one of said target track, a power supply voltage, a temperature, a spindle motor back electromotive force, and a positioner gain.

19.   The disk drive, as claimed in claim 18, wherein said variable amount is calculated according to the equation:

$$Derate\_\text{factor} = \frac{(\text{max\_track} - \text{tgt\_track})^2 \times 127}{2^{26} \times \sqrt{2a}} + 0.5$$

where *max_track* is the number of a track with a predefined relationship to said

5   ramp, *tgt_track* is the number of the target track, and *a* is the deceleration of said

transducer.

20.   A disk drive, as claimed in claim 19 wherein said first velocity profile is

further limited according to the following equation:

$$Vel = \sqrt{2a} \times \sqrt{(1 + \text{Kwarp} \times \text{Vel}) \times \text{xtg}}$$

5   where *a* is the deceleration of said transducer, *Vel* is the velocity of said

transducer, *xtg* is the distance from said starting track to said target track, and *kwarp* is a

variable determined by an amount of back electromotive force available from said voice

coil motor during deceleration of said actuator arm.

21.   A method for changing radial position of a transducer relative to a rotating

storage medium from a starting track to a target track, comprising:

determining a desired velocity profile for said transducer as a function of radial

position of said transducer, said velocity profile including at least an acceleration portion

5   and a deceleration portion;

adjusting at least said deceleration portion of said velocity profile based on at least

a direction of travel of said transducer; and

moving said transducer from said starting track to said target track in accordance

with said velocity profile.

22.   A method, as claimed in claim 20, wherein said adjusting step includes:

determining a direction of travel of said transducer from said target track to a

maximum track; and

derating at least said deceleration portion of said velocity profile when said

5   direction of travel is toward said maximum track.

23.   A method, as claimed in claim 22, wherein:

said maximum track is located near an inner diameter of said rotating storage

medium.

24.   A method, as claimed in claim 22, wherein:

said maximum track is located near an outer diameter of said rotating storage

medium.

25.   A method, as claimed in claim 21, wherein said adjusting step includes:

determining a first distance from said target track to a maximum track;

determining a velocity that said transducer will achieve;

determining a direction of travel of said transducer; and

5   derating said velocity profile when said first distance is less than a first

predetermined number, said velocity is greater than a maximum safe velocity, and said

direction of travel is toward said maximum track.

26.   A method, as claimed in claim 25, wherein:

said derating step includes adjusting at least said deceleration portion by a

predetermined amount.

27.   A method, as claimed in claim 26, wherein:

said predetermined amount is 50 percent of a current available for said

deceleration portion.

28.   A method, as claimed in claim 25, wherein:

said derating step includes adjusting at least said deceleration portion by a

variable amount.

29.   A method, as claimed in claim 28, wherein said variable amount is

determined according to at least one of said target track, a power supply voltage, a

temperature, a spindle motor back electromotive force, and a positioner gain.

30.   A method, as claimed in claim 29, wherein said variable amount is a

derate factor determined by the equation equation:

$$Derate\_ \text{factor} = \frac{(\text{max\_track} - \text{tgt\_track})^2 \times 127}{2^{26} \times \sqrt{2a}} + 0.5$$

where *max_track* is the number of the maximum track, *tgt_track* is the number of

the target track, and *a* is the deceleration of the transducer according to said deceleration

portion of said seek velocity profile.

31.　A method, as claimed in claim 29, wherein:

said derating step further includes calculating a warping factor and applying said

warping factor to said velocity profile.

32.　A method, as claimed in claim 31, wherein:

said warping factor is determined based on at least one of said first distance and a

back electromotive force of a voice coil motor during said deceleration portion.

33.　A method, as claimed in claim 32, wherein said warping factor is

determined according to the following equation:

$$Warp\_\ factor = \sqrt{2a} \times \sqrt{(1 + Kwarp \times Vel) \times xtg}$$

where *a* is the deceleration of said transducer according to said deceleration

portion of said seek velocity profile, *vel* is the velocity of the transducer, *xtg* is the

distance between said starting track and said target track, and *kwarp* is a variable

determined by the amount of said back electromotive force.

34.   A disk drive, comprising:

a storage disk having a plurality of concentric tracks for storing data including at

least a first track located at an outer diameter of said storage disk and a second track

located at an inner diameter of said storage disk;

5   a spindle motor for rotating said storage disk;

an actuator arm assembly having a transducer for reading data from said storage

disk and a ramp tab;

a ramp operable to engage said ramp tab and prevent said transducer from

contacting said storage disk when said storage disk is not rotating;

10   a voice coil motor operable to move said actuator arm relative to said storage disk

in response to a control signal; and

a controller operable to generate said control signal and deliver said control signal

to said voice coil motor such that said actuator arm moves in a direction from a starting

track to a target track according to a seek velocity profile, wherein said seek velocity

15   profile includes at least an acceleration portion and a deceleration portion, and said seek

velocity profile is derated based on at least a direction of travel of said actuator arm.

35.   The disk drive, as claimed in claim 34, wherein:

at least said deceleration portion of said seek velocity profile is derated by a factor

of 0.5 when said actuator arm moves toward said ramp and said target track is within a

predefined distance from said ramp.

-34-

36.   The disk drive, as claimed in claim 35, wherein:

at least said deceleration portion of said seek velocity profile is derated by a

variable amount when said actuator arm moves toward said ramp and said target track is

within a predefined distance from said ramp.

37.   The disk drive, as claimed in claim 36, wherein:

said variable amount is determined based on at least one of said target track, a

power supply voltage, a temperature, a spindle back electromotive force, and a positioner

gain.

38.   The disk drive, as claimed in claim 37, wherein said variable amount is

derate factor determined by the equation:

$$Derate\_factor = \frac{(max\_track - tgt\_track)^2 \times 127}{2^{26} \times \sqrt{2a}} + 0.5$$

where *max_track* is the number of a track with a predefined relationship to said

ramp, *tgt_track* is the number of the target track, and *a* is the deceleration of said

transducer during said deceleration portion of said seek velocity profile.

39.   The disk drive, as claimed in claim 38, wherein:

max_track is the number of said second track when said ramp is located at said

inner diameter of said storage disk.

40.   The disk drive, as claimed in claim 38, wherein:

max_track is the number of said first track when said ramp is located at said outer

diameter of said storage disk.

41.   A disk drive, as claimed in claim 37, wherein said variable amount also

includes a warping factor based on at least one of a seek length and a back electromotive

force of said voice coil motor.

42.   A disk drive, as claimed in claim 41, wherein said warping factor is

determined according to the equation:

$$Warp\_\ \text{factor} = \sqrt{2a} \times \sqrt{(1 + \text{Kwarp} \times \text{Vel}) \times \text{xtg}}$$

5   where *a* is the deceleration of said transducer according to said deceleration

portion of said seek velocity profile, *Vel* is the velocity of said transducer, *xtg* is the

distance from said starting track to said target track, and *kwarp* is a variable determined

by an amount of back electromotive force available from said voice coil motor during

said deceleration portion of said seek velocity profile.

43.   A disk drive, comprising:

storage means for storing data;

rotation means for rotating said storage means;

read/write means for reading and writing data to said storage means;

-36-

5   actuation means for moving said read/write means from a starting location to a

target location within said storage means; and

control means for controlling said actuation means such that said actuation means

move said read/write means according to a first velocity profile when said starting

location is a first direction from said target location, and according to at a second velocity

10   profile when said starting location is a second direction from said target location and said

target location is within a predefined distance from a reference location within said

storage means.

44.   The disk drive, as claimed in claim 43, wherein:

said reference location is located at an inner diameter of said storage means.

45.   The disk drive, as claimed in claim 43, wherein:

said reference location is located at an outer diameter of said storage means.

46.   The disk drive, as claimed in claim 43, wherein:

at least a deceleration portion of said second velocity profile is derated by a

predefined factor of said first velocity profile.

47.   The disk drive, as claimed in claim 46, wherein:

said predefined factor is one-half.

48.   The disk drive, as claimed in claim 43, wherein:

said second velocity profile is derated by a variable factor of said first velocity profile.

49.   The disk drive, as claimed in claim 43, wherein:

said variable factor is determined based on at least one of said target location, a power supply voltage, a temperature, a back electromotive force of said rotation means, and a positioner gain.

50.   The disk drive, as claimed in claim 48, wherein said variable factor is determined according to the following equation:

$$Derate\_ \text{factor} = \frac{(ref\_loc - tgt\_loc)^2 \times 127}{2^{26} \times \sqrt{2a}} + 0.5$$

5   where *ref_loc* is the number of the reference location, *tgt_loc* is the number of the target location, and *a* is the deceleration of said read/write means during a deceleration portion of said second velocity profile.

51.   The disk drive, as claimed in claim 49, wherein:

said variable factor is further determined based on a warping factor, wherein said warping factor is determined based on at least one of a seek length and a back electromotive force of said actuation means.

52. The disk drive, as claimed in claim 49, wherein said warping factor is determined according to the following equation:

$$Warp\_ \text{factor} = \sqrt{2a} \times \sqrt{(1 + \text{Kwarp} \times \text{Vel}) \times \text{xtg}}$$

5   where a is the deceleration of said read/write means during said deceleration portion of said second velocity profile, Vel is the velocity of said read/write means, xtg is the distance from said starting location to said target location, and $kwarp$ is a variable determined by an amount of back electromotive force available from said actuation means during said deceleration portion of said second velocity profile.